



RP-8700

VOLTAGE CHART OF EACH TRANSISTORS

	Q101	Q102	Q103	Q104	Q301	Q302	Q303	Q304	Q305	Q306	Q701	
C	AM	0	0	4.6	4.2	0	3.8	3.6	4.0	0	4.0	4.6
	FM	4.2	4.3	0	0	4.0	3.8	3.6	4.0	4.0	4.0	4.6
B	AM	0	0	1.1	1.05	0	0.9	1.0	1.1	0	0.6	0.7
	FM	0.9	0.9	0	0	0.95	0.9	1.0	1.1	1.05	0.6	0.7
E	AM	0	0	0.5	0.5	0	0.25	0.4	0.4	0	0.1	0.25
	FM	0.25	0.3	0	0	0.3	0.25	0.4	0.4	0.45	0.1	0.25

NOTES 1. All voltage are measured from common negative (-) ground.
 2. Volume control is at the minimum position.

Integrated Circuit IC 701, 702

	NO 1	NO 2	NO 3	NO 4	NO 5	NO 6	NO 7
AM	3.0	0	0	4.3	0.8	3.0	0
FM	3.0	0	0	4.3	0.8	3.0	0

	NO 8	NO 9	NO 10	NO 11	NO 12	NO 13	NO 14
AM	2.4	3.0	3.1	0	5.8	5.9	6.0
FM	2.4	3.0	3.1	0	5.8	5.9	6.0

NOTES 1. All voltages are measured from common negative (-) ground.
 2. Volume control is at the minimum position.