



5A-10型 配線圖並に部分品定數

使用部分品表

抵抗類	R-1	可變抵抗器	20 k Ω		C-10	筒型紙蓄電器	0.1 μ F	耐壓 1000V
	R-2	カーボン抵抗	400 Ω	1/3 W	C-11	"	0.00016 "	"
	R-3	"	10 k Ω	1/3 "	C-12	"	0.01 "	"
	R-4	"	50 "	1 "	C-13	"	0.1 "	"
	R-5	"	160 "	1/3 "	C-14	"	0.004 "	"
	R-6	"	250 "	1/3 "	C-15~20	ブロック型電解蓄電器		
	R-7	"	50 "	1/3 "			10, 10, 2, 4, 8, 4 μ F	50 V 350 V
	R-8	"	250 "	1/3 "	その他	L-1, 2	空中線線輪	
	R-9	"	800 Ω	1 "		L-3, 4	高周波線輪	
	R-10	"	3.2 k Ω	2 "		L-5, 6	検波線輪	
蓄電器類	C-1~6	三連可變蓄電器	50~350 μ F			T ₂	出力變成器	
	C-7	筒型紙蓄電器	0.01 μ F	耐壓 1000V		L ₇	音響線輪	
	C-8	"	0.01 "	"		L ₈	高聲器断磁線輪	
	C-9	"	.01 "	"		T ₁	單巻變壓器	

5A-10 型 配線圖



